

INVERSORES ONDA PURA



Model /Ideal	PI-600	PI-1000	PI-1500	PI-2000	PI-3000
Output power (Continuos Watts)	5~600	1000	1500	2000	3000
Output power (Peak Watts)	1200	2000	3000	4000	6000
Standby Current	< 1.0 A				
Nominal Input Voltage (DC)	12V(11V-15V)/24V(22V-30V)/48V (44V-60V)				
Nominal Output Voltage (AC)	100VAC	110 VAC	115VAC	120VAC	220 VAC 230 VAC 240 VAC
Frequency	50 Hz 60Hz +/-3Hz				
Output Regulation	5% Intelligent Pwm				
Output Waveform	Pure sine Wave				
Low Battery -Voltage Alarm (Volts)	10,5+/-0.5V/21 V+/-1V/42+/-1V				
Low Battery -Voltage Shutdown (Volts)	10+/-0.5 V/20 V+/-1V/40V+/-1V				
High Battery -Voltage Shutdown (Volts)	16+/-1V/32V+/-2V/62V+/-2v				
Efficiency	85-90%				
Pure since wave output	THD <3%				
Thermal Protection	< 65°C				
Overload	Shut Down				
Battery Polarity Reverse	By Fuse				
Output Short	Output Short Circuit Protection				
With Cooling Fan	Yes				
AC Outlets Plug	Universal				
Replaceable Fuse	2X30A/2X15A/ 2X10A	4X30A/4X10 A	6X30A/6X15A /6X10A	12X30A/12X15 A/12X10A	16x30A/16X15 A/16X10A
Dimension (L*W*H)cm	190*125*70	272*220*78	328*220*82.7	343*206*92	381.5*206*92
Weight	1.05 Kg	2.6Kg	3.5Kg	5.2Kg	6.15 Kg